

# QEP S6 50Hz 1p AVR ITR 12V

QEP Range



Genset image for illustration purposes only


## Technical data

Voltage	(V)	230
Frequency	(Hz)	50
Fuel		Diesel
Performance class		G1
Acoustic pressure LpA	(dB(A) @7m)	65
Acoustic power LwA	(dB(A))	93

## Mechanical structure

Length (L)	(mm)	990
Width (W)	(mm)	602
Height (H)	(mm)	826
Weight	(kg)	186
Fuel tank capacity	(l)	24
Wheels and handles		Optional

## Dimensions



Note: These drawings are provided for illustration purposes only.

## Power ratings

Prime	Prime	Standby	Standby
kW	kVA	kW	kVA
4.3	4.8	5.3	5.9
Power factor			0.9

## Fuel consumption table

Load level	PRIME (L/h)	Aut. (h)
75%	1.46	16.44
100%	1.94	12.37

## Engine

### General

Engine Brand		Yanmar
Engine Model		L100
R.P.M.		3000
Net Power	(kWm)	6.50
Fuel		Diesel
No. of cylinders		1
Displacement	(cm³)	435
Regulation type		Mechanic

### Lubrication System

Oil capacity	(l)	1.6
Engine Oil Guard		YES

### Cooling System

Cooling type		Air
--------------	--	-----

### Starting system

Recoil	NO
Electric 12V	YES

## Alternator

Alternator brand		NSM
Alternator model		KR100G AVR
IP alternator		IP23
Peak power 163°/27°	(kVA)	6.48
Poles		2
Excitation system		AVR
		Brushes
Efficiency at 100% 125°/40°	(%)	77

## Mains features and options

### Mains features

- Electrical key start (12V)
- Large fuel tank
- Engine Oil Guard
- Automatic Voltage Regulation (AVR)
- Circuit breaker
- Instrumentation, voltmeter, hourmeter
- Insulation monitoring relay (ITR)
- Lifting frame
- Canopy soundproof
- Sockets
- CE noise compliance

### Sockets configuration

SCHUKO 230V 16A IP54	1
2P+T CEE 230V 16A IP44	1
2P+T CEE 230V 32A IP44	1

### Options

- Wheel kit

## Regulations:

The generator set has a CE Marking that includes the following directives:

- 2006/42/CE Machine Safety.
- 2006/95/CEE Low Voltage.
- 2004/108/CE Electromagnetic compatibility.
- 97/68/CE Gases and contaminating particles emissions.

### Definitions

#### Prime Rating

PRIME POWER: Electrical power data available at a variable load without limits of hours per year. An overload of 10 % is allowed for 1 hour of every 12. In accordance with ISO 8528/1 (2005) – PRP

#### Standby

STANDBY POWER: Electrical power data at variable load in an emergency in accordance with standard ISO 8528/1 (2005) – ESP. Overloads of emergency power are not allowed.

Grupos Electr genos Europa, S.A. is a certified company with ISO 9001, ISO 14001, OHSAS 18001 and PECAL

Atlas Copco reserves the right to modify any characteristic of their equipment without prior warning.

All products are designed and engineered in Zaragoza Competence Center

Weight and dimensions of a standard generator set.

Non-contractual document

Grupos Electr genos Europa, S.A.

Central Offices:

Pol gono pitarco II - Parcela 20

50450 Muel (Zaragoza) Espa a

Tel.: +34 976 145 432

Fax.: +34 976 145 431

DISTRIBUTED BY:



Please, contact your local Atlas Copco Dealer for more information